

GENERATING SET GE 3000 SX

- Honda OHV gasoline engine
- Engine protection (oil)
- Single phase synchronous alternator
- Suitable for electronic equipment
- Recessed sockets
- Circuit breaker / GFI - ELCB
- Protective frame
- Complies with EEC directives



| | | | | | | | | | | |
|-------------------------------|------------------------|-----------------|--------------------|------------------|--------------------------|-----------------|--|--|--|--|
| Standard equipment | | | | | | | | | | |
| | Gasoline engine | Air cooling | Manual recoil | Oil alert | Engine shut down (oil) | | | | | |
| | | | | | | | | | | |
| | Synchronous alternator | Socket 230V EEC | Socket schuko 230V | Thermal shut off | Ground fault interrupter | Battery charger | | | | |

Options on request

- Plug 230V 16A 2PT (M)
- Battery cables set
- Earthing Kit MT10

Technical Data GE 3000 SX

| | |
|---|--|
| A.C. GENERATION | 50 Hz, synchronous, single-phase, self-excited, self-regulated, brushless |
| Single-phase generation | 2.5 kVA (2 kW) / 230 V / 10.8 A |
| Battery charge d.c. | 12V - 10A |
| Duty cycle | 100% |
| Power factor (cos φ) | 0.9 |
| Insulation class | H |
| On request other voltages and frequencies (60 Hz) | |

| | |
|--|---------------------------------------|
| ENGINE | Gasoline, 4-stroke, air cooled |
| Type | HONDA GX 160 K1 |
| Output* | 3.3 kW (4.5 HP) |
| Speed | 3000 rpm |
| Displacement | 163 cm ³ |
| Cylinders | 1 |
| Fuel consumption | 313 g/kWh |
| * Maximum output according to ISO 3046/1 | |

| | |
|--------------------------------------|-------------------------|
| GENERAL SPECIFICATIONS | |
| Tank capacity | 3.6 l |
| Running time (Load 75%) | 3.5 h |
| Protection | IP 23 |
| Dimensions Lxwxh (mm) | 570x420x450 |
| Weight | 50 kg |
| Noise level ** | 96 LWA (71 dB(A) - 7 m) |
| ** LWA conforms to EEC Directive 536 | |

Values shown are nominal values. For further information please contact the sales department.