

## GENERATING SET GE 7554 BS/GS - E

- Honda OHV gasoline engine
- Three-phase synchronous alternator **"IP 54"**
- Electronic voltage regulator
- Asymmetric load **200%**
- Protections: Overload Circuit Breaker and Ground Fault Interrupter
- Engine shut off-oil
- Wrap around protective frame
- Meets EEC directives



Standard equipment									
	Gasoline engine	Air cooling	Manual recoil	Hour counter	Engine shut down (oil)				
	Synchronous alternator	Electronic voltage regulator	Voltmeter	3~EEC Socket 400V EEC	1~EEC Socket 230V EEC	Circuit breaker	Ground fault interrupter		

- Options on request**
- Plug 400V 16A 3PNT (T)
  - Plug 230V 16A 2PT (M)
  - Earthing Kit MT10
  - Trolley CTM200
  - Kit exhaust extension PS 4.5

### Technical Data GE 7554 BS/GS - E

**A.C. GENERATION** 50 Hz, synchronous, three-phase, self-excited, self-regulated

Generator power	8 kVA / 400 V / 11,5 A
Three-phase generation	7,5 kVA / 230 V / 10,8A
Single-phase generation	5 kVA / 230 V / 21,7 A
<b>Protection</b>	<b>IP 54</b>
Reinforce phase (Cos φ)	3 0.8

**ENGINE** Gasoline, 4-stroke, air cooled

Output*	Honda GX 390
Speed	8.4 kW (11.4 HP)
Displacement	3000 rpm
Cylinders	389 cm <sup>3</sup>
Fuel consumption	1
	313 g/kWh

\* Maximum output according to ISO 3046/1

**GENERAL SPECIFICATIONS**

Tank capacity	6.5 l
Running time (Load 75%)	3 h
Protection	IP 43
Dimensions Lxwxh (mm) *	910x525x613
Weight *	88 kg
Noise level **	99 LWA(74 dB(A) - 7 m)

\* Dimensions and weight are inclusive of all parts without optional CTM. \*\* LWA conforms to EEC Directive 536

**Values shown are nominal values. For further information please contact the sales department.**